

MP3 Repair Guide

1. Basic

Product	MP3	Model Name	YP-U5
Buyer	All buyer	Index NO	MP3-R041

2. Symptoms

Booting Error, No Power, Malfunction

- Booting Error : When you turn on the unit, it stop and halt booting.
- No Power : ① Charging the battery ② Upgrade firmware with recovery program ③ Check the PBA and the battery
- Malfunction : the Display halts and any key is not operated.

3. Cause

Soft Error

- ; Firmware has damage or work abnormally
- When Customer upgrades the unit with new version, he does with the wrong process or disconnect with PC while firmware upgrading.

4. Method

<input type="checkbox"/> Component Repair			<input type="checkbox"/> Firmware Update	
Loc' no	Spec.	Parts Code	Before	After
			-	Recovery Update

 [Next page](#)

YP-U5 Recovery Update

- when normal update is impossible
- when the set can't power on
- when the set operates abnormally.

2009.04.09

When Recovery update is needed?

1. Symptom

- Power on/off doesn't work.
- YP-U5 doesn't connect to computer when insert USB.
- Display is not normal. .
- You can not access removable Disk (YP-U5).

2. Solution


A. General F/W Upgrade

B. Recovery F/W Upgrade


- Firmware has damage or work abnormally.

Step 1. Recovery Update

1. Download Recovery program and decompress on your PC



2. Execute "U5_updater.exe".
Display "please connect device".




Step 1. Recovery Update

3. Connect YP-U5 with pushing & holding "User Key" to PC, display "initial" and then "Ready".




4. Select "Format data area", "full Media Erase" and file system: FAT32, then push the "Start" button.




Step 1. Recovery Update

5. Start to update, and then pop up the format message, please chooses "Yes"




6. Update completed.
7. Disconnect YP-U5 from the USB, check that YP-U5 display "Updating", YP-U5 will be turn on automatically.
8. Check all function.
9. Step 1 completed.




Step 2. AUI(Audio User Interface) Update

1. Download the "YP-U5_AUI" and decompress on your PC



※ The folder contents are like side :



2. Connect YP-U5 to PC and copy "YP-U5_AUI" folder to YP-U5.
3. Disconnect YP-U5 from the USB ; check that YP-U5 display "Updating".
(When battery level is not enough, "Updating" can not execute. Please try after charging.)
4. Turn on and check booting sound of AUI.
5. Step 2 completed.

Step 3. Regional Configuration Update

1. When you change regional configuration, download the “Config.dat”.

And look for your country folder

Folder	Country	Type	Firmware Region Ex) ver 1.XX US	Basic Language
USA	US, Canada, Australia, New Zealand	MTP	US	English
Europe	Europe	MTP	EU	English
France	France	MTP	FR	French
China-S	China	UMS	CN	Simplified Chinese
China-T	Hongkong, Taiwan	UMS	CN	Traditional Chinese
Japan	Japan	UMS	JP	Japanese
Russia	Russia	UMS	RU	Russian Language
Turkey	Turkey	UMS	TR	English
World Wide	World Wide (other countries)	UMS	WA	English

2. Copy the “Config.dat” to YP-U5.

3. Disconnect YP-U5 from the USB,
check that YP-U5 display “Updating”,
YP-U5 will be turn on automatically.

4. Turn on and check F/W regional version
in “Settings → System → About”

5. All step completed.

